

SPECIFICATION

TO ALL WHOM IT MAY CONCERN:

BE IT KNOWN THAT I, TATSUYA FUKUNISHI, a citizen of Japan residing at Kanagawa, Japan have invented certain new and useful improvements in

SECONDARY BATTERY CONTROL CIRCUIT

of which the following is a specification:-

700050:5075360

1. Field of the Invention

discharge control technology of a secondary battery

10 More particularly, the present invention
relates to a secondary-battery control circuit, a
battery pack including the secondary-battery control
circuit and a portable device using the battery pack,
wherein the secondary-battery control circuit is
15 suitable to a battery management system having a
remaining-charge indicating IC (Integrated Circuit) used
for indicating a remaining charge, or a resetting IC
used for resetting the battery management system when a
power source has a predetermined voltage, the IC being a
20 typical SBM (Smart Battery Management).

A lithium-ion or lithium-polymer secondary battery is widely used in various areas of technologies such as portable devices including a cellular phone, a laptop computer, and a videotape recorder with a built-

in camera. The secondary battery is often used as a battery system, by being combined with a remaining-charge indicating IC that indicates a remaining charge of the secondary battery, or a resetting IC that
5 monitors a source voltage of the battery system and outputs a reset signal resetting the battery system when the source voltage becomes a predetermined voltage.

FIG. 1 is a circuit diagram showing a related art of the battery system described above. The related-
10 art battery system shown in FIG. 1 includes a secondary battery 201, a protection circuit 202, a system terminal 203, cutoff switches 204 and 204'. The protection circuit 202 controls charge and discharge of the secondary battery, and protects the secondary battery
15 from a damage caused by overcharge. The system terminal 203 is a terminal connected to a system that includes load circuits such as a re-charger, the remaining-charge indicating IC, and the resetting IC. The cutoff switches 204 and 204' are FETs (Field Effect
20 Transistors) that cut off a charging or discharging path between the secondary battery and the above-described system including the re-charger and various load circuits, when the secondary battery is over-charged or over-discharged.

25 The protection circuit 202 (the secondary-

00000105-050001

According to the above-described functions of
15 the protection circuit 202 (the secondary-battery
control circuit 2), the related-art battery system shown
in FIG. 1 prevents destruction of the secondary battery
and a circuit on the system side.

On other hand, in the case in which the power supply from the secondary battery to the system is cut off, the system must select a unit among a plurality of units, and stop an operation of the unit, in accordance with a reason for the power supply being cut off. Thus, the system must use a circuit consisting of external components for providing the power supply to the

The above-described related art has problems described below.

However, in a related-art technology, the power supply from the secondary battery to all the circuits including the remaining-charge indicating IC and the resetting IC is cut off, when the overcharge, the over-discharge or the excess current is detected, even in a case in which the remaining voltage of the secondary battery is higher than the lowest operational voltages of the units other than the remaining-charge indicating IC and the resetting IC. Consequently, the remaining-charge indicating IC and the resetting IC cannot function appropriately.

To solve the above-described problem, the related-art battery system shown in FIG. 1 takes steps to supply the power from the secondary battery to the remaining-charge indicating IC and the resetting IC

Usage of the related-art battery system using the
5 external components cannot avoid increases in a total
mounting area of the battery system and a production
cost.

According to the related-art battery system as described above, the power supply from the secondary battery to the system is cut off when the overcharge, the over-discharge, or the excess current is detected. The battery system using the lithium-ion or lithium-polymer secondary battery is demanded to control monitoring of a voltage condition of the secondary battery in detail, for instance, an overcharging or over-discharging condition, because of characteristics of the battery pack. On the other hand, the battery system is demanded to continue operations performed by the remaining-charge indicating IC or the resetting IC while monitoring a current condition such as the excess current.

The related-art battery system utilizes a method of using the external components, in order to satisfy the above-described demands from the system side. However, according to such a method, the number of the

10

15

20

25

The above-described objects of the present invention are achieved by a secondary-battery control circuit, including a first path supplying a first load current from one or more secondary batteries connected in series or parallel, to a system, and including a first cutoff switch; and a second path supplying a second load current from the one or more secondary batteries to the system, wherein the first cutoff switch is turned off if a voltage of the one or more secondary batteries is lower than a first predetermined voltage, or if the first load current is greater than a predetermined current, thereby cutting off the first load current to the system.

The above-described objects of the present invention are also achieved by a battery pack, including one or more secondary batteries connected in series or parallel; and a secondary-battery control circuit, wherein the secondary-battery control circuit includes a first path supplying a first load current from the one or more secondary batteries to a system, and including a

The above-described objects of the present invention are also achieved by a portable device including a battery pack that includes one or more secondary battery connected in series or parallel, and a secondary-battery control circuit; and a load circuit supplied with a load current from the battery pack, wherein the secondary-battery control circuit includes a first path supplying a first load current from one or more secondary batteries connected in series or parallel to a system, and including a first cutoff switch; and a second path supplying a second load current from the one or more secondary batteries to the system, wherein the first cutoff switch is turned off if a voltage of the one or more secondary batteries is lower than a first predetermined voltage, or if the first load current is greater than a predetermined current, thereby cutting off the first load current to the system.

In a related-art secondary-battery control circuit, a circuit, which is used for supplying the power from a secondary battery to units such as a remaining-charge indicating IC and a resetting IC on a system side selectively, is provided as an external component. On the other hand, according to the present invention, reduction of the total mounting area and the cost of the secondary-battery control circuit is achieved by including such a circuit in the secondary-battery control circuit. Additionally, reliability of the secondary-battery control circuit and accuracy of setting values are improved by including the circuit in the secondary-battery control circuit.

Additionally, by providing another power supply path (the second path) in addition to a related-art power supply path (the first path) to the system including units such as the remaining-charge indicating IC and the resetting IC, in the secondary-battery control circuit, the secondary-battery control circuit can improve the accuracy and the flexibility of the setting values.

Other objects, features and advantages of the present invention will become more apparent from the following detailed description when read in conjunction with the accompanying drawings.

0054105-000004

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a circuit diagram showing a related-art battery system;

FIG. 2 is a circuit diagram showing a
5 secondary-battery control circuit according to the
present invention;

FIG. 3 is a circuit diagram showing an operation performed by the secondary-battery control circuit in a case of charging a secondary battery;

10 FIG. 4 is a circuit diagram showing an
operation performed by the secondary-battery control
circuit in a case of discharging the secondary battery;
and

FIG. 5 is a circuit diagram showing a
15 structure of a protection circuit shown in FIGS. 2, 3
and 4.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

A description will now be given of preferred
20 embodiments of the present invention, with reference to
the accompanying drawings.

FIG. 2 is a circuit diagram showing a secondary-battery control circuit according to the present invention. The secondary-battery control circuit shown in FIG. 2 includes a secondary battery 1,

5 FET 51 and a FET 52.

20 second cutoff switch 61.

25 battery 1, or an excess current is detected. The system

terminal "b" is connected to units, for example, a remaining-charge indicating IC and a resetting IC that must keep operating even if a remaining charge of the secondary battery 1 becomes lower than the lowest operational voltage of the units connected to the system terminal "a".

A description will now be given of operations performed by the secondary-battery control circuit in the cases of charging and discharging the secondary battery 1. FIG. 3 is a circuit diagram showing the operation performed by the secondary-battery control circuit in the case of charging the secondary battery 1. FIG. 4 is a circuit diagram showing the operation performed by the secondary-battery control circuit in the case of discharging the secondary battery 1. In addition, FIG. 5 is a circuit diagram showing a structure of the protection circuit 2 shown in FIGS. 2, 3 and 4.

The protection circuit 2 shown in FIG. 5 includes standard-voltage generating circuits (standard voltage circuits) 101, 105 and 107, sense-voltage generating circuits (sense voltage circuits) 102, 106 and 108, an overcharge detecting unit 103, an over-discharge detecting unit 104, logic gates (logical addition gates) 109, 110, 115 and 116, logic circuits

0054105-050904
F06090-5075660

111, 112, 113, 114 and 117, delay circuits D1 through D5, and a plurality of comparators C.

The cutoff voltage of the first cutoff switch 5 (the FETs 51 and 52) connected to the system terminal "a" is specified by the standard-voltage generating circuits 101 and 107. Additionally, the cutoff voltage of the second cutoff switch 6 (the FET 61) connected to the system terminal "b" is specified by the standard-voltage generating circuit 105.

10 In the charging operation shown in FIG. 3, a re-charger 7 is connected between the system terminal "a" and a ground voltage GND. Additionally, a remaining-charge indicating IC 9 and a resetting IC 10 are connected between the system terminal "b" and the
15 ground voltage GND. On the other hand, in the discharging operation shown in FIG. 4, a load circuit 8 is connected between the system terminal "a" and the ground voltage GND. Additionally, the remaining-charge indicating IC 9 and the resetting IC 10 are connected
20 between the system terminal "b" and the ground voltage GND.

A description will initially be given of an operation performed by the secondary-battery control circuit in the case of charging the secondary battery 1,
25 with reference to FIG. 3. When the re-charger 7 is

TOP SECRET

connected to the system terminal "a", a charging current flows from the re-charger 7 to the secondary battery 1, and, then, the secondary battery 1 starts being charged. In a case in which a voltage of the secondary battery 1 is higher than the cutoff voltage of the second cutoff switch 6 (the FET 61), the remaining-charge indicating IC 9 and the resetting IC 10 keep operating, which have been connected to the system terminal "b" before the re-charger 7 is connected to the system terminal "a".

10 In a case in which the voltage of the secondary battery 1 is lower than the cutoff voltage of the second cutoff switch 6, the second cutoff switch 6 is turned off. However, when the voltage of the secondary battery 1 exceeds the cutoff voltage of the cutoff switch 6 as the secondary battery 1 is charged, the second cutoff switch 6 is turned on. In detail, in a case in which a comparator C determines that a voltage at the system terminal "b" detected by the sense-voltage generating circuit 106 is higher than a standard voltage generated by the standard-voltage generating circuit 105, a signal indicating that the voltage at the system terminal "b" is higher than the standard voltage is supplied through the delay circuit D5 and the logic circuit 117, to the second cutoff switch 6.

25 Consequently, the second cutoff switch 6 is turned on.

2025 RELEASE UNDER E.O. 14176

5

10

25

10

15

20

25

detected by the sense-voltage generating circuit 102 is less than the standard voltage generated by the standard-voltage generating circuit 101, a signal indicating that the voltage of the secondary battery 1 is less than the standard voltage is supplied through the logic gate 110, the delay circuit D2, the logic circuit 112 and the logic gate 115, to the first cutoff switch 5 (the FET 51). Consequently, the first cutoff switch 5 (the FET 51) is turned off.

10 Accordingly, the power supply from the secondary battery 1 to the load circuit 8 is stopped. However, the second cutoff switch 6 (the FET 61) is still turned on, since the cutoff voltage of the second cutoff switch 6 (the FET 61) is less than that of the first cutoff switch 5 (the FET 51). Thus, the remaining-charge indicating IC 9 and the resetting IC 10 connected to the system terminal "b" continues operating, and, for instance, performs the process to calculate and display the voltage capacity of the secondary battery 1.

20 Subsequently, when the discharging process of the secondary battery 1 continues, and the voltage of the secondary battery 1 becomes less than the cutoff voltage of the second cutoff switch 6 (the FET 61), the second cutoff switch 6 (the FET 61) is turned off.

25 Consequently, the remaining-charge indicating IC 9 and

0054105-050904

the resetting IC 10, which are connected through the system terminal "a" to the second cutoff switch 6 (the FET 61), cannot be supplied with the power from the secondary battery 1, and stop operating. It should be
5 noted that the FET 52 of the first cutoff switch 5 is turned on during the above-described operation.

A description will now be given of an operation performed by the secondary-battery control circuit when detecting an excess current. In a case in
10 which an excess current whose value being higher than charge/discharge excess-current setting values predetermined in the protection circuit 2 flows through the secondary battery 1 or the first cutoff switch 5, the first cutoff switch (the FET 51 or the FET 52) is turned
15 off. In detail, if it is determined, by comparing the standard voltage generated by the standard-voltage generating circuit 107 and the voltage detected by the sense-voltage generating circuit 108, that the excess current flows while the secondary battery 1 is being
20 charged, a signal is supplied to the first cutoff switch 5 (the FET 52) through the delay circuit D3, the logic circuit 113 and the logic gate 116, indicating that the excess current flows while the secondary battery 1 is being charged. Consequently, the first cutoff switch 5
25 (the FET 52) is turned off.

005405-050904
406050-507500

On the other hand, if it is determined, by comparing the standard voltage generated by the standard-voltage generating circuit 107 and the voltage detected by the sense-voltage generating circuit 108, that the excess current flows while the secondary battery 1 is being discharged, a signal is supplied to the first cutoff switch (the FET 51) through the delay circuit D4, the logic circuit 114 and the logic gate 115, indicating that the excess current flows while the secondary battery 1 is being discharged. Consequently, the first cutoff switch 5 (the FET 51) is turned off.

In other words, if the excess current flows while the secondary battery 1 is being charged, a path between the secondary battery 1 and the re-charger 7 is cut off because of the FET 52 being turned off. On the other hand, if the excess current flows while the secondary battery 1 is being discharged, a path between the secondary battery 1 and the load circuit 8 is cut off because of the FET 51 being turned off. Accordingly, the battery system is protected from damages caused by the excess current.

However, the second cutoff switch 6 is not turned off as long as the voltage of the secondary battery 1 is higher than the cutoff voltage of the second cutoff switch 6 (the FET 61) even if the excess

00000105-050001

5 If the secondary battery 1 includes a plurality of secondary batteries, each of the standard-voltage generating circuit 101, the sense-voltage generating circuit 102, the overcharge detecting unit 103 and the over-discharge detecting unit 104 has a structure to achieve the above-described functions for each secondary battery included in the secondary battery 1. For instance, if the plurality of secondary batteries are connected in series in the secondary battery 1, the overcharge detecting unit 103 or the over-discharge detecting unit 104 compares a voltage of each secondary battery detected by the sense-voltage generating circuit 102, with a standard voltage generated by the standard-voltage generating circuit 101 for each secondary battery. If the overcharge detecting unit 103 or the over-discharge detecting unit 104 detects at least an overcharged secondary battery or an over-discharged secondary battery among the plurality of the secondary batteries, the FET 52 or the FET 51 is turned off respectively through the logic gates 109 and 110.

Additionally, FIG. 5 shows a pair of the standard-voltage generating circuit 101 and the sense-voltage generating circuit 102, and a pair of the standard-voltage generating circuit 107 and the sense-voltage generating circuit 108, for the purpose of simplifying FIG. 5. However, in detail, two pairs of the standard-voltage generating circuit 101 and the sense-voltage generating circuit 102, and two pairs of the standard-voltage generating circuit 107 and the sense-voltage generating circuit 108 are provided in the protection circuit 2. One pair of the standard-voltage generating circuit 101 and the sense-voltage generating circuit 102 is used for detecting the overcharge of the secondary battery 1, and the other pair of the standard-voltage generating circuit 101 and the sense-voltage generating circuit 102 is used for detecting the over-discharge of the secondary battery 1. On the other hand, one pair of the standard-voltage generating circuit 107 and the sense-voltage generating circuit 108 is used for detecting the excess current while the secondary battery 1 is being charged, and the pair of the standard-voltage generating circuit 107 and the sense-voltage generating circuit 108 is used for detecting the excess current while the secondary battery 1 is being discharged.

In a related-art battery system or secondary-

battery control circuit, a circuit, which is used for supplying the power from a secondary battery to units such as a remaining-charge indicating IC and a resetting IC on a system side selectively, is provided as an
5 external component. On the other hand, according to the present invention, reduction of the total mounting area of the battery system and the cost is achieved by including such a circuit in the secondary-battery control circuit. Additionally, reliability of the
10 protection circuit and accuracy of setting values are improved by including the circuit in the protection circuit.

Additionally, by providing another power supply path in addition to a related-art power supply
15 path to the system including units such as the remaining-charge indicating IC and the resetting IC, in the secondary-battery control circuit, the secondary-battery control circuit can improve the accuracy and the flexibility of the setting values.

20 Further, in the case of detecting the overcharge of the secondary battery, or the excess current while the secondary battery is being charged or discharged, the secondary-battery control circuit can achieve a system reset operation and an operation to
25 display the voltage capacity of the secondary battery,

0005405 050904
F00000 507000

by use of the remaining-charge indicating IC and the resetting IC.

Additionally, by including the secondary-battery control circuit according to the present invention in a battery pack, and the battery pack in a portable device, the battery pack and the portable device can achieve the reduction of the total mounting areas of the battery pack and the portable device, and the reduction of the costs. Such a battery pack and a portable device can further improve the reliability of the battery pack and the portable device, and the accuracy of the setting values, by including the circuit, which is an external component in the related-art secondary-battery control circuit, in the protection circuit of the secondary-battery control circuit according to the present invention.

The above description is provided in order to enable any person skilled in the art to make and use the invention and sets forth the best mode contemplated by the inventors of carrying out the invention.

The present invention is not limited to the specially disclosed embodiments and variations, and modifications may be made without departing from the scope and spirit of the invention.

The present application is based on Japanese

095405-05094
F00050-50F5060

Priority Application No. 2000-142884, filed on May 16, 2000, the entire contents of which are hereby incorporated by reference.

0954105:050901